



# Criomix 500 II

## Overview

**Criomix 500 II** is a compact 4 Channel Dj mixer with 1 microphone input, 2 stereo line/phone inputs, 2 stereo line inputs and 1 USB connection. The unit provides precise control over your mix thanks to its 3-band EQ per channel and crossover fader. **Criomix 500 II** has a balanced master output and VU meter per channel.

## Specifications

### General

Stereo channels: 4  
 Mono channels: 1  
 Frequency response: 20Hz-20KHz  
 THD: <0.07%, +4 dBu @ 1KHz, unity gain  
 Signal-to-Noise ratio: >82dB  
 Microphone input with independent level control & 3-band equalization  
 Adjustable CUE mix  
 Precise crossfader

### Per channel

Phono/Line selector

Gain, HF, MF & LF control  
 Equalization range: -26dB/+12dB  
 CUE button  
 Crossfader assign

### Connections

1 XLR-TRS Combo balanced Microphone Input  
 1 TRS 1/4" Plug Microphone Input  
 2 dual-RCA Phono Inputs  
 4 dual-RCA Line Inputs  
 1 USB Input  
 2 XLR-3 Balanced Master Outputs

1 dual-RCA Master Output  
 1 dual-RCA Booth Output  
 1 dual-RCA REC Output

### Electrical

Input voltage range: AC100–240V, 50-60Hz  
 Power consumption: 18W

### Physical

Dimensions: 254x295x104 mm. /  
 10x11.6x4.10 in.  
 Weight: 2.8 Kg. / 6.17 Lbs.