



# Navigator

## Overview

**Navigator** is a DMX controller with 192 DMX channels able to control up to 12 fixtures of 16 DMX channels each. The unit has a total of 30 banks with 8 programmable scenes. It also includes 6 chases of 240 programmed scenes from 30 banks, MIDI control over banks, chases and blackout. Thanks to its pan and tilt jog wheels it's easy to create complex effects.

## Specifications

### Interface

Backlit LCD display  
8 faders for manual control - 2 pages  
2 Jog Wheels - PAN and TILT  
Blackout master button

### Features

19 DMX channels - 12 fixtures of 16 DMX channels  
30 banks of 8 programmable scenes

6 chases of 240 programmed scenes from 30 banks  
Fade Time/Assign Fade Time  
Manual override  
DMX polarity select  
Fog machine input and trigger button

### Connections

2 3-pin XLR connectors: DMX input/output  
1 DIN connector: Midi in

1 DIN connector: Fog machine  
1 RCA: Audio in  
1 Built-in microphone for music sync functions  
1 Power input

### Physical

Dimensions: 482x132x73 mm. / 19x5.2x2.87 in.  
Weight: 2.5 Kg. / 5.5 Lbs.