



Criomix 100 II

Overview

Criomix 100 II is a compact 2 Channel Dj mixer with 1 microphone input and 2 stereo line/phone inputs. The unit provides precise control over your mix thanks to its 3-band EQ per channel and crossover fader. **Criomix 100 II** has an unbalanced master output and its ideal for small scale events or installations.

Specifications

General

Stereo channels: 2
Frequency response: 20Hz-20KHz
THD: <0.05%, +4 dBu @ 1KHz, unity gain
Line: 80dB
Phono: 70dB
Mic: 75dB
Microphone input with independent level control
Selectable Talkover & PFL assign
Precise crossfader

Per channel

Phono/Line selector
Gain, HF & LF control
Equalization
- LF: $\pm 2\text{dB}/100\text{Hz}$
- HF: $\pm 2\text{dB}/100\text{Hz}$
- Talkover: -24dB

Connections

1 TRS 1/4" Plug Microphone Input
2 dual-RCA Phono Inputs

2 dual-RCA Line Inputs
1 dual-RCA Master Output
1 dual-RCA REC Output

Electrical

Input voltage range: AC100–240V,
50-60Hz

Physical

Dimensions: 164x218x77 mm. /
6.5x8.6x3 in.
Weight: 1.2 Kg. / 2.6 Lbs.