



Navigator 24

Overview

Navigator 24 is a DMX dimming controller with 24 DMX channels and 2-scenes operation, providing 4200 programmable scenes plus 48 programmable chases. The unit has 24 individual faders and 24 bump buttons, easily configurable to provide pile on chase, blind & dark.

Specifications

Interface

- 3-digit LED display
- 24 faders for manual control
- 2-scene operation
- 24 bump buttons
- Tap Sync button for chase/fade override
- Full-on button – 100% intensity in all channels

Features

- 24 DMX channels
- 4200 programmable scenes

- 48 programmable chases
- Solo function
- Pile on chase, Blind & Dark
- Speed control
- Fog machine input and trigger button
- Manual override
- DMX polarity select

Connections

- 1 3-pin XLR connector: DMX output
- 3 DIN connectors: Midi in/Thru/Out
- 1 RCA: Audio in

- 1 1/4" Stereo Plug: Remote control
- 1 1/4" Stereo Plug: Flash trigger
- 1 Power input

Physical

- Dimensions: 300x152x75 mm. / 11.8x6x2.95 in.
- Weight: 2.10 Kg. / 4.60 Lbs.